

How to use the EBUS to USB Mini Adapter Board to flash modules:

This process requires Prism Version 4.9.4 or later and properly installed USB drivers.

1. Disconnect other EBUS devices from module to be updated.
2. Connect Adapter Board to computer with the USB cable and to module with one of the EBUS cables.
3. Ensure appropriate HEX file is in the Prism2 folder on your computer.
4. In Prism2, click “Communications”, “Flash Selected Controller” and select “Manual Flashing”
5. Click “Connection”, “Direct”
6. Choose the appropriate HEX file:
Use the “...” button to navigate to the Prism2 folder to locate the HEX file and double-click the file.
7. Enter the appropriate EBUS address for your specific module:

MODGAS-X	138	MODGAS-XWR(-1)	138 for 1 st board, 139 for 2 nd board
MHGRV-X	132	RSMD/RSMV	152/153/154/155
WSHP-X2	17	SMSD/HHSD	62
PREHEAT-X	157		
8. Click “Reset Ebus” button then click “Program HEX” button. The process may take a minute or two.
9. The bottom bar of the window will note that the process is completed.